

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 0 801 506 A2

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
15.10.1997 Bulletin 1997/42

(51) Int. Cl.⁶: H04N 7/30

(21) Application number: 97200913.8

(22) Date of filing: 26.03.1997

(84) Designated Contracting States:
DE FR GB

(30) Priority: 10.04.1996 US 630553

(71) Applicant: EASTMAN KODAK COMPANY
Rochester, New York 14650 (US)

(72) Inventors:
• Gandhi, Bhavan R.
Rochester, New York 14650-2201 (US)

• Rabbani, Majid
Rochester, New York 14650-2201 (US)
• Miller, Rodney L.
Rochester, New York 14650-2201 (US)

(74) Representative: Blickle, K. Werner, Dipl.-Ing. et al
KODAK AKTIENGESELLSCHAFT
Patentabteilung
70323 Stuttgart (DE)

(54) **A method and apparatus for suppressing blocking artifacts in block-transform coded images**

(57) An improved method for removing blocking artifacts in regions of slowly varying intensity in an electronic image decoded from a transform coded representation of an image, includes the steps of: receiving signals indicative of DC and AC coefficient values of transformed blocks of image data; modifying the DC value in each of the blocks based on the level of activity within the block and the DC values in neighbor-

ing blocks; performing AC prediction in each block using the modified DC values; replacing the AC values in each block with the AC predicted values based on the level of activity within the block and the modified DC values in neighboring blocks; and reconstructing the image using the modified DC and AC coefficient values.




FIG. 2

Description**Field of Invention**

5 The invention relates generally to the field of image processing and, more particularly, to removing artifacts resulting from block-transform coded images.

Background Of The Invention

10 Various numerically lossy compression methods are used in digital image processing to compress image data prior to transmission from one computer workstation to another computer workstation where the image data is decompressed (i.e., reconstructed). A well-known compression method employs a discrete cosine transform (DCT), such as lossy JPEG (Joint Photographic Expert Group) international standard.

15 In this regard, a digital representation of an image is divided into a plurality of non-overlapping, contiguous 8x8 blocks of pixel data. Each non-overlapping 8x8 pixel block of image data is then transformed, via the DCT, from a pixel representation space into a DCT representation space. Each transformed block of image data is comprised of one DC coefficient and 63 AC coefficients. The DC coefficient represents the average brightness of the block and the AC coefficients represent the spatial frequency information in the block.

20 During the coding process, the DC and AC coefficients for each block are quantized and encoded into a bit-stream prior to any transmission to another computer workstation. Quantization, in effect, introduces numerical loss by mapping a range of coefficient values to one value, which mapping is referred to hereinafter as a quantization level. Encoding assigns a binary code to the resulting set of quantized values. At the receiving workstation, the bit-stream is decoded and dequantized to reconstruct the set of dequantized coefficient values. These dequantized coefficients are subsequently transformed back into the pixel representation space via an inverse discrete cosine transform (IDCT), as
25 is well known in the art.

At the compression workstation, the number of bits generated by the compression process corresponds, in part, to the number of quantization levels used in the quantization. Using a fewer number of quantization levels, coarse quantization, will generate a fewer number of bits than a less coarse quantization. However, coarse quantization introduces undesirable blocking artifacts at the decoding workstation. Coarse quantization may increase the disparity between the
30 DC coefficients of neighboring blocks, and it may destroy low frequency AC coefficient information within a block. This results in a blocking artifact which is visually more objectionable in regions of slowly varying intensity.

As used herein, an image region is said to be "busy" if it contains high spatial frequency texture and edge detail. Conversely, an image region is said to be "quiet" if it contains relatively low spatial frequency texture and edge detail as is the case in regions of slowly varying intensity.

35 A standard technique for reducing blocking artifacts is known as AC prediction, such as that disclosed by Mitchell, J.L. and W.B. Pennebaker "JPEG ENHANCEMENTS" Still Image Data Compression Standard 1993, page 261-265, and is applied at the decompression workstation. AC prediction for low frequency AC coefficients is formed using dequantized DC coefficients from the current block and its eight nearest neighbor blocks. The AC predicted coefficient values for the block replace the corresponding dequantized AC coefficient values prior to transforming the image back
40 into the pixel representation space. One shortcoming of this technique is that the AC predicted coefficients replace the dequantized AC coefficient values regardless of the block activity or, in other words, whether the block is in a "busy" area or a "quiet" area. This has the undesirable tendency of visually smoothing out high frequency image detail or "busy" areas in the block, and of introducing low frequency AC information which has no effect in reducing the disparity of dequantized DC coefficients between neighboring blocks.

45 An adaptive method for reducing blocking artifacts is disclosed in an European Patent Application 0585573A2 by De Garido et. al. An adaptive AC Predictor is based on a prescribed activity measure of the current image block and its eight nearest neighbor blocks. This technique, unlike the above-described method, does not introduce low frequency information via AC prediction in "busy" areas; thus, high spatial frequency and texture information which is indicative of high activity blocks is preserved. This adaptive AC prediction technique still has the disadvantage of not reducing the
50 disparity of the dequantized DC coefficients between neighboring blocks in low activity image areas.

Consequently, a need exists for improvements in the decompression of block-transform coded images so as to overcome the above-described drawbacks.

Summary Of The Invention

55 The present invention is directed to overcoming one or more of the problems set forth above. Briefly summarized, according to one aspect of the present invention, an improved method for removing blocking artifacts in regions of slowly varying intensity in an electronic image decoded from a transform coded representation of an image, includes the steps of: receiving signals indicative of quantized DC and AC coefficient values of transformed blocks of image data;

dequantizing the quantized coefficient values; modifying the DC value in each of the blocks based on the level of activity within the block and the DC values in neighboring blocks; replacing the AC values in each block with the AC predicted values based on the level of activity within the block and the modified DC values in neighboring blocks; and reconstructing the image using the modified DC and AC coefficient values.

It is an object of the present invention to overcome the above-described shortcomings.

It is another object of the present invention to apply the invention without requiring a change to the standard nature of a JPEG compressed bit-stream.

It is a feature of the present invention to provide modifying the DC value in each of the blocks based on the level of activity within the block and the DC values in neighboring blocks.

It is an advantage of the present invention to provide a method which may either be implemented via software or hardware for performing the invention.

These and other aspects, objects, features and advantages of the present invention will be more clearly understood and appreciated from a review of the following detailed description of the preferred embodiments and appended claims, and by reference to the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a schematic diagram of a computer system for implementing the present invention;

Fig. 2 is a block diagram of the decompression system according to the current invention utilizing an improved block artifact reduction technique;

Fig. 3 is a block diagram of an alternative decompression system according to the present invention utilizing an improved block artifact reduction technique; and

Fig. 4 is a detailed block diagram of the method used to modify the DC coefficients.

DETAILED DESCRIPTION OF THE INVENTION

In the following description, the present invention will be described in the preferred embodiment as a software program. Those skilled in the art will readily recognize that the equivalent of such software may also be constructed in hardware.

Referring to Fig. 1, there is shown a system for implementing the present invention. A digital camera 10, such as a "KODAK" DC 50, includes a charge-coupled device, CCD (not shown), for receiving incident light through a lens 20, and for converting the incident light into an electronic, digital representation of an image 25 that is contained within the incident light, as is well known in the photographic industry. The CCD transfers the electronic representation of the image to a personal computer card (PCC) 30 for storing the image for later retrieval.

However, before storage of the image on the PCC 30, JPEG compression software which is stored on a memory module (not shown) of the camera 10 is used for compressing the digital representation of the image received from the CCD. Such compression is desirable for limiting the amount of memory necessary for storing the digital representation of the image on the PCC 30.

The PCC 30 is inserted into a local computer or workstation 40 for permitting the representation of the image to be decompressed and viewed on a monitor 50 that is electrically connected to the local computer 40. Alternatively, the digital representation of the image 25, which is still in compressed form, may be transmitted to another remote computer or workstation 60 where it is decompressed for viewing on a monitor 70, printing by a printer (not shown) or further processing by a remote user. For decompressing the digital representation of the image, a software program of the present invention is stored both on the local computer 40 and the remote computer 50 for decompressing the digital representation of the image while also reducing the occurrence of blocking artifacts for permitting such viewing.

Referring now to Fig. 2, there is shown a graphical illustration of the software program of the present invention for reducing the occurrence of artifacts in the image when it is reconstructed. It is instructive to note that this software receives the image in a form which has been compressed by lossy JPEG compressor. A standard JPEG-encoded, compressed bit-stream, E_{bs} , is decoded via a decoder 80 to form signals representative of quantized DC and AC coefficient values of a plurality of transformed blocks of image data,

$$[Q_{ij}]_{mn}$$

The decoder 80 also decodes and produces a quantization table Q_{tab} representing the quantization that was applied at the compressor workstation 60 to the DC and AC coefficient values of each block. The quantized coefficient values,

$$[Q_{ij}]_{mn}$$

are subsequently dequantized using the quantization table, Q_{tab} , by a dequantizer 85 to form dequantized coefficient values of a plurality of transformed blocks of image data,

$$[Z_{ij}^Q]_{mn}$$

It facilitates understanding to note that the subscripts i and j index the coefficient values within a block where both i and j take on numerical values ranging from 0 to 7 inclusively. Index values of $i=0$ and $j=0$ correspond to the DC coefficient value in the block. Index values of $i \neq 0$ or $j \neq 0$ correspond to the AC coefficient values in the block. Furthermore, the subscripts m and n denote the horizontal and vertical position of a block 90 from the plurality of blocks respectively. The ij and mn subscript notation herein be used as described to denote coefficient values within the block and locations of the block respectively.

The plurality of dequantized transformed blocks of image data,

$$[Z_{ij}^Q]_{mn}$$

are input to an ADAPTIVE DC CORRELATOR 100 to reduce the disparity between DC coefficients of neighboring blocks. The ADAPTIVE DC CORRELATOR 100, described in detail below, modifies the reconstructed DC coefficient of each block,

$$[Z_{00}^Q]_{mn}$$

based on an activity measure (also described below) of the block and eight nearest neighbor blocks to form transformed blocks of image data with modified DC coefficients,

$$[Z_{ij}^{QD}]_{mn}$$

The modified DC coefficients

$$[Z_{00}^{QD}]_{mn}$$

are used by an ADAPTIVE AC PREDICTOR 110 to form adaptive AC predictions (as is well known in the art) for low frequency AC coefficients in the block. The equations describing the predicted AC coefficient values are:

$$[Z_{01}^{QM}]_{mn} = (1.13885 / 8) ([Z_{00}^{QD}]_{m-1, n} - [Z_{00}^{QD}]_{m+1, n}); \quad (1)$$

$$[Z_{10}^{QM}]_{mn} = (1.13885 / 8) ([Z_{00}^{QD}]_{m, n-1} - [Z_{00}^{QD}]_{m, n+1})$$

$$[Z_{20}^{QM}]_{mn} = (0.27881 / 8) ([Z_{00}^{QD}]_{m, n-1} + [Z_{00}^{QD}]_{m, n+1} - 2[Z_{00}^{QD}]_{mn});$$

$$[Z_{11}^{QM}]_{mn} = (1.13885 / 8) \{ ([Z_{00}^{OD}]_{m-1, n-1} - [Z_{00}^{OD}]_{m+1, n-1}) \cdot ([Z_{00}^{OD}]_{m-1, n+1} - [Z_{00}^{OD}]_{m+1, n+1}) \};$$

$$[Z_{02}^{OM}]_{mn} = (0.27881 / 8) \{ [Z_{00}^{OD}]_{m-1, n} + [Z_{00}^{OD}]_{m+1, n} - 2[Z_{00}^{OD}]_{mn} \}.$$

The output of the ADAPTIVE AC PREDICTOR 110 is transformed blocks of image data with modified DC and AC coefficients,

$$[Z_{ij}^{QM}]_{mn}$$

The modified DC and AC coefficient values in each block

$$[Z_{ij}^{QM}]_{mn}$$

are made consistent by an AC/DC CONSISTENCY CHECK module 120. The AC/DC CONSISTENCY CHECK module 120 with inputs

$$[Z_{ij}^{QM}]_{mn}, [Q_{ij}]_{mn}$$

and the quantization table, Q_{tab} produces a consistent set of DC and AC coefficient values which are denoted as

$$[Z_{ij}^{QC}]_{mn}$$

The DC and AC coefficient values in each block

$$[Z_{ij}^{QM}]_{mn}$$

are consistent if, when quantized by the corresponding Q_{tab} entry, they result in quantized DC and AC coefficient values which are the same as those in

$$[Q_{ij}]_{mn}$$

If

$$[Z_{ij}^{QM}]_{mn}$$

is not consistent, the AC/DC CONSISTENCY CHECK module 120 increases or decreases the appropriate coefficient values in each block

$$[Z_{ij}^{QM}]_{mn}$$

until the corresponding DC and AC coefficient values are made consistent. This method of consistency checking intro-

duces the smallest magnitude change of the coefficient values. The consistent blocks of DCT representative data,

$$\left[z_{ij}^{QC} \right]_{mn},$$

are then transformed back into a pixel representation space by a well-known INVERSE DCT module 130 to form blocks of reconstructed image data,

$$\left[I' \right]_{mn}.$$

An alternate preferred embodiment of the present invention is shown in Figure 3. The modules in Figure 3 which are equivalently numbered to those modules in Figure 2 are functionally identical. The embodiment in Figure 3 is comprised of an additional DC CONSISTENCY CHECK module 105, and an AC CONSISTENCY CHECK module 115, but does not include the combined AC/DC CONSISTENCY CHECK module 120 (shown in Figure 2). The DC CONSISTENCY CHECK module 105 takes inputs

$$\left[z_{ij}^{QD} \right]_{mn}, \left[Q_{ij} \right]_{mn},$$

and Q_{lab} and makes

$$\left[z_{00}^{QD} \right]_{mn}$$

consistent with

$$\left[Q_{00} \right]_{mn}$$

in the same manner described for the AC/DC CONSISTENCY CHECK module 120 (shown in Figure 2) to produce

$$\left[z_{ij}^{QD'} \right]_{mn}.$$

The AC CONSISTENCY CHECK module 115 takes inputs

$$\left[z_{ij}^{QM'} \right]_{mn}, \left[Q_{ij} \right]_{mn},$$

and Q_{lab} and makes the AC coefficients (i.e., $i \neq 0$ or $j \neq 0$) consistent with

$$\left[Q_{ij} \right]_{mn}.$$

in the same manner described for the AC/DC CONSISTENCY CHECK module 120 (shown in Figure 2) to produce

$$\left[z_{ij}^{QC'} \right]_{mn}.$$

As is well known in the art, the reconstructed image data may be used by any suitable computing station, such as workstations 40 or 60, to transform the image data into a hardcopy image that has reduced blocking artifacts, particularly in regions of slowly varying intensity.

A detailed block diagram of the ADAPTIVE DC CORRELATOR 100 is shown in Fig. 4. Dequantized transformed blocks of image data,

$$\left[z_{ij}^Q \right]_{mn}$$

are passed to the EXTRACT DC COEFFICIENT module 140 which extracts the DC coefficient from each block which is denoted as

$$\left[z_{00}^Q \right]_{mn}$$

The DC low pass filter (LPF) module 150 generates a low pass filtered version of the

$$\left[z_{00}^Q \right]_{mn}$$

denoted as

$$\left[z_{(0)}^Q \right]_{mn}$$

by convolving

$$\left[z_{00}^Q \right]_{mn}$$

with a low pass filter denoted as [B].

$$\left[z_{(0)}^Q \right]_{mn} = \sum_{q=-1}^1 \sum_{p=-1}^1 \left(\left[z_{00}^Q \right]_{m+p, n+q} \right) B_{pq} \quad (2)$$

In the preferred embodiment the low pass filter 150, [B], is a 3x3 element matrix with the following coefficients:

$$[B] = \begin{bmatrix} 1/16 & 1/16 & 1/16 \\ 1/16 & 8/16 & 1/16 \\ 1/16 & 1/16 & 1/16 \end{bmatrix} ; \quad p=-1, 0, 1 \text{ and } q=-1, 0, 1. \quad (3)$$

The elements of [B] are referenced as B_{pq} with subscripts p and q corresponding to the horizontal and vertical location of the matrix elements with top left element being identified with p=-1 and q=-1.

An alternate embodiment of the low pass filtering operation denoted by equation (2) is given by equation (4).

$$[Z_{00}^Q]_{mn} = \left[\sum_{p=-1}^1 ([Z_{00}^Q]_{m+p,n-1}) B_{p,-1} \right] + ([Z_{00}^Q]_{m-1,n}) B_{-1,0} + \left[\sum_{q=0}^1 \sum_{p=0}^1 ([Z_{00}^Q]_{m+p,n+q}) B_{pq} \right] + ([Z_{00}^Q]_{m-1,n+1}) B_{-1,1} \quad (4)$$

5 This alternative filtering process uses previously filtered coefficient values for modifying the current coefficient value.
A COMPUTE BLOCK ACTIVITY module 160 determines the activity for each dequantized transformed block of image data,

$$[Z_{ij}^Q]_{mn}$$

The output of this module 160 is an activity indicator, α , which takes on values greater than or equal to 0.0 and less than 1.0. Each block

$$[Z_{ij}^Q]_{mn}$$

20 is comprised of one DC coefficient (for $i=0$ and $j=0$) value and 63 AC coefficient values (for $i \neq 0$ or $j \neq 0$). The nomenclature illustrated in block 90 is an alternate representation of

$$[Z_{ij}^Q]_{mn}$$

illustrating the diagonal zig-zag ordering as defined by the JPEG international standard; the index k represents the AC coefficient's index. Each AC_k coefficient value in a block is examined and determined if the coefficient takes on a zero or a non-zero value. Each index of k with a non-zero coefficient value is stored in memory (not shown). The stored indices are retrieved from memory and the maximum index value k is determined and is denoted as k_{nz} . The activity measure α is calculated by taking the ratio of k_{nz} and the numerical value 64.

$$\alpha = k_{nz} / 64 \quad (5)$$

The numerical value 64 in the denominator of equation (5) corresponds to the total number of DC and AC coefficient values in a block. The k_{nz} value may also be obtained by reading the end of block (EOB) indicator from the decoder as defined in the JPEG standard, as is known by those skilled in the art. There are also other techniques known in the art that may be used to compute the activity of a transformed block of image data as will be readily apparent by those skilled in the art.

In conjunction with the computing of the activity of a block 90, a maximum local gradient is computed between the DC coefficient of a block 90 and the DC coefficient from its eight nearest neighbors by the COMPUTE MAXIMUM LOCAL GRAD module 170. This module 170 determines the maximum absolute value difference between the DC value of the current block and the DC values of the eight nearest neighbor blocks as denoted by Δ_{max} .

$$\Delta_{max} = \text{MAX}(|[Z_{00}^Q]_{m+u,n+v} - [Z_{00}^Q]_{mn}|) \quad (6)$$

For all integer values of u and v such that,
-1 $\leq u \leq 1$, and -1 $\leq v \leq 1$.

The original dequantized DC values

$$[Z_{00}^Q]_{mn}$$

low pass filtered DC values

$$\left[z_{00}^Q \right]'_{mn}$$

the activity measure α , and the maximum local gradient Δ_{\max} are inputs to an ADAPTIVE FILTER module 180 to generate an adaptively filtered DC coefficient,

$$\left[z_{00}^{QF} \right]_{mn}$$

The ADAPTIVE FILTER module 180 adaptively combines the

$$\left[z_{00}^Q \right]_{mn} \text{ and } \left[z_{00}^Q \right]'_{mn}$$

coefficients to produce

$$\left[z_{00}^{QF} \right]_{mn}$$

according to the following logic:

If ($\Delta_{\max} < \Delta_{\text{Thresh}}$)

$$\left[z_{00}^{QF} \right]_{mn} = \alpha \left[z_{00}^Q \right]_{mn} + (1 - \alpha) \left[z_{00}^Q \right]'_{mn}$$

Else

$$\left[z_{00}^{QF} \right]_{mn} = \left[z_{00}^Q \right]_{mn}$$

Where Δ_{Thresh} is a user defined value and is preferably set to 256 for pixel representative data which has a binary representation of 8 bits per pixel for the JPEG baseline. According to the above logic, the low pass filtered DC coefficient

$$\left[z_{00}^Q \right]'_{mn}$$

is combined with the original dequantized DC coefficient

$$\left[z_{00}^Q \right]_{mn}$$

only if Δ_{\max} is less than Δ_{Thresh} . This is a switching mechanism which allows the adaptive filtering to be invoked in image regions for slowly varying intensity. The adaptively filtered DC coefficient

$$\left[z_{00}^{QF} \right]_{mn}$$

replaces

$$\left[z_{00}^Q \right]_{mn}$$

by the INSERT DC COEFFICIENT module 190 to produce a block of quantized transform representative data with a modified DC coefficient,

$$\left[z_{ij}^{QD} \right]_{mn}$$

As shown in Figure 2,

$$\left[z_{ij}^{QD} \right]_{mn}$$

is an input to the ADAPTIVE AC PREDICTOR module 110 as previously described; and as shown in Figure 3,

$$\left[z_{ij}^{QD} \right]_{mn}$$

is an input to the DC CONSISTENCY CHECK module 105.

Parts List:

10	camera
20	lens
25	image
30	personal computer card (PCC)
40	workstation
50	monitor
60	workstation
70	monitor
80	decoder
90	block
100	adaptive DC correlator
110	adaptive AC predictor module
120	consistency check module
130	inverse DCT module
140	extract DC coefficient
150	low pass filter
160	compute block activity
170	compute maximum local grad module
180	adaptive filter module
190	insert DC coefficient module

Claims

1. An improved method for removing blocking artifacts in regions of slowly varying intensity in an electronic image decoded from a transform-coded representation of an image, the method comprising the steps of:
 - (a) receiving signals indicative of DC and AC coefficient values of transformed blocks of image data;
 - (b) dequantizing the quantized coefficient values;
 - (c) modifying the DC value in each of the blocks based on the level of activity within the block and the DC values in neighboring blocks;
 - (d) replacing the AC values in each block with the AC predicted values based on the modified DC values in the block and in neighboring blocks; and
 - (e) reconstructing the image using the modified DC and AC coefficient values.
2. The method as in claim 1, wherein step (c) further comprises computing the activity level by identifying a highest AC coefficient index that represents a non-zero frequency component in the block.
3. The method as in claim 1, wherein step (c) further comprises computing the activity level by calculating a maximum absolute value difference between the DC value of a block and its eight nearest neighbors for forming a local gradient.
4. The method as in claim 1, wherein step (c) further comprises modifying the DC value by convolving a low pass filter with the DC coefficients derived from the received transformed blocks of image data and replacing the DC coefficient derived from the received transformed blocks of image data with the convolved DC coefficient if a predetermined criterion is met.
5. The method as in claim 4, wherein the predetermined criterion includes determining when the local gradient is less than a threshold.
6. The method as in claim 1 further comprising performing adaptive AC prediction on the result of step (d).
7. The method as in claim 1 further comprising performing a consistency check of the results of the modified DC values and AC predicted values.
8. A computer for receiving signals indicative of DC and AC coefficient values of transformed blocks of image data and for removing artifacts of slowly varying intensity from the image data, the computer comprising:
 - (a) means for dequantizing coefficient values;
 - (b) means for modifying the DC value in each of the blocks based on the level of activity within the block and the DC values in neighboring blocks; and
 - (c) means for replacing the AC values in each block with the AC predicted values based on the level of activity within the block and the modified DC values in neighboring blocks.
9. The computer as in claim 8 further comprising means for computing the activity level by identifying a highest AC coefficient index that represents a non-zero frequency component in the block.
10. The computer as in claim 8 further comprising means for computing the activity level by calculating a maximum absolute value difference between the DC value of a block and its eight nearest neighbors for forming a local gradient.




FIG. 1




FIG. 2





FIG. 3



$$[Z_{ij}^Q]_{mn} = \begin{bmatrix} [Z_{oo}^Q]_{mn} & AC_1 & AC_2 & \dots & AC_6 & \dots \\ & AC_4 & AC_3 & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & & \end{bmatrix} \quad \begin{matrix} \vdots \\ \vdots \\ \vdots \\ \vdots \\ \vdots \\ \vdots \end{matrix}$$

90

FIG. 4

THIS PAGE BLANK (USPTO)

(19)



Europäisches Patentamt

European Patent Office

Office européen des brevets



(11)

EP 0 801 506 A3

(12)

EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
22.12.1999 Bulletin 1999/51

(51) Int. Cl.⁶: H04N 7/30

(43) Date of publication A2:
15.10.1997 Bulletin 1997/42

(21) Application number: 97200913.8

(22) Date of filing: 26.03.1997

(84) Designated Contracting States:
DE FR GB

(30) Priority: 10.04.1996 US 630553

(71) Applicant: EASTMAN KODAK COMPANY
Rochester, New York 14650 (US)

(72) Inventors:
• Gandhi, Bhavan R.
Rochester, New York 14650-2201 (US)

• Rabbani, Majid
Rochester, New York 14650-2201 (US)
• Miller, Rodney L.
Rochester, New York 14650-2201 (US)

(74) Representative:
Blickle, K. Werner, Dipl.-Ing. et al
KODAK AKTIENGESELLSCHAFT
Patentabteilung
70323 Stuttgart (DE)

(54) **A method and apparatus for suppressing blocking artifacts in block-transform coded images**

(57) An improved method for removing blocking artifacts in regions of slowly varying intensity in an electronic image decoded from a transform coded representation of an image, includes the steps of: receiving signals indicative of DC and AC coefficient values of transformed blocks of image data; modifying the DC value in each of the blocks based on the level of activity within the block and the DC values in neighbor-

ing blocks; performing AC prediction in each block using the modified DC values; replacing the AC values in each block with the AC predicted values based on the level of activity within the block and the modified DC values in neighboring blocks; and reconstructing the image using the modified DC and AC coefficient values.




FIG. 2



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 97 20 0913

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
Y	TIEN C -N ET AL: "TRANSFORM-DOMAIN POSTPROCESSING OF DCT-CODED IMAGES" SPIE VISUAL COMMUNICATIONS AND IMAGE PROCESSING, vol. 2094, no. PART 03, 8 November 1993 (1993-11-08), pages 1627-1638, XP002057987 section 4 "Inter-block transform coefficient adjustment" * figures 10-14 *	1-10	H04N7/30
D,Y	EP 0 585 573 A (IBM) 9 March 1994 (1994-03-09) * page 3, line 51 - line 5 * * abstract; figure 4 *	1-10	
A	EP 0 422 404 A (IBM) 17 April 1991 (1991-04-17) * column 4, line 5 - line 55 * * column 7, line 13 - column 11, line 30 * * abstract; figures 5,6 *	1-10	
A	GONZALES C A: "DCT CODING FOR MOTION VIDEO STORAGE USING ADAPTIVE ARITHMETIC CODING" SIGNAL PROCESSING. IMAGE COMMUNICATION, vol. 2, no. 2, 1 August 1990 (1990-08-01), pages 145-154, XP000243474 ISSN: 0923-5965 section 2.2 "Decoding algorithms" * abstract; figures 2-4 *	1-10	TECHNICAL FIELDS SEARCHED (Int.Cl.6) H04N
A	US 5 146 326 A (HASEGAWA MAKOTO) 8 September 1992 (1992-09-08) * column 6, line 43 - column 9, line 2 * * column 9, line 28 - column 11, line 24 * * abstract; figures 4-6,9-11 *	1-5,8-10	
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 29 October 1999	Examiner La, V
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document		T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document	

EPO FORM 1503 03/82 (P04C01)



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 97 20 0913

DOCUMENTS CONSIDERED TO BE RELEVANT

Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
A	EP 0 680 217 A (DAE WOO ELECTRONICS CO LTD) 2 November 1995 (1995-11-02) * page 4, line 7 - line 25 * * abstract; figure 1 * -----	1,7	
			TECHNICAL FIELDS SEARCHED (Int.Cl.6)
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 29 October 1999	Examiner La, V
CATEGORY OF CITED DOCUMENTS X: particularly relevant if taken alone Y: particularly relevant if combined with another document of the same category A: technological background O: non-written disclosure P: intermediate document T: theory or principle underlying the invention E: earlier patent document, but published on, or after the filing date D: document cited in the application L: document cited for other reasons & member of the same patent family, corresponding document			

EPO FORM 1503 03 82 (P04C01)

ANNEX TO THE EUROPEAN SEARCH REPORT ON EUROPEAN PATENT APPLICATION NO.

EP 97 20 0913

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

29-10-1999

Patent document cited in search report		Publication date	Patent family member(s)		Publication date
EP 0585573	A	09-03-1994	NONE		

EP 0422404	A	17-04-1991	US	5001559 A	19-03-1991
			DE	69026896 D	13-06-1996
			JP	2618083 B	11-06-1997
			JP	3139988 A	14-06-1991

US 5146326	A	08-09-1992	JP	3155280 A	03-07-1991
			JP	3167962 A	19-07-1991

EP 0680217	A	02-11-1995	KR	128881 B	10-04-1998
			CN	1112335 A	22-11-1995
			JP	2859830 B	24-02-1999
			JP	7322262 A	08-12-1995
			US	5606372 A	25-02-1997

DRM P0459

EPO FORM P0459

For more details about this annex, see Official Journal of the European Patent Office, No. 12/82